

d ... konstanta 1 zleblka  
 w ... konstanta 2 zleblky  
 a ... adresa zleblky

00	NOP	27	DAA	4C	MOV C,H	6F	MOV L,A	92	SUB D	B5	ORA L	DA	JC	a
01	LXI B,w	29	DAD H	4D	MOV C,L	70	MOV M,B	93	SUB E	B6	ORA M	DB	IN	d
02	STAX B	2A	LHLD a	4E	MOV C,M	71	MOV M,C	94	SUB H	B7	ORA A	DC	CC	a
03	INX B	2B	DCX H	4F	MOV C,A	72	MOV M,D	95	SUB L	B8	CMP B	DE	SBI	d
04	INR B	2C	INR L	50	MOV D,B	73	MOV M,E	96	SUB M	B9	CMP C	DF	RST	3
05	DCR B	2D	DCR L	51	MOV D,C	74	MOV M,H	97	SUB A	BA	CMP D	E0	RPO	
06	MVI B,d	2E	MVI L,d	52	MOV D,D	75	MOV M,L	98	SBB B	BB	CMP E	E1	POP H	
07	RLC	2F	CMA	53	MOV D,E	76	HLT	99	SBB C	BC	CMP H	E2	JFO	a
09	DAD B	30	...	54	MOV D,H	77	MOV M,A	9A	SBB D	BD	CMP L	E3	XTHL	
0A	LDAX B	31	LXI SP,w	55	MOV D,L	78	MOV A,B	9B	SBB E	BE	CMP M	E4	CPO	a
0B	DCX B	32	STA a	56	MOV D,M	79	MOV A,C	9C	SBB H	BF	CMP A	E5	PUSH H	
0C	INR C	33	INX SP	57	MOV D,A	7A	MOV A,D	9D	SBB L	C0	RNZ	E6	ANI	d
0D	DCR C	34	INR M	58	MOV E,B	7B	MOV A,E	9E	SBB M	C1	POP B	E7	RST	4
0E	MVI C,d	35	DCR M	59	MOV E,C	7C	MOV A,H	9F	SBB A	C2	JNZ a	E8	RPE	
0F	RRC	36	MVI M,d	5A	MOV E,D	7D	MOV A,L	A0	ANA B	C3	JMP a	E9	PCHL	
11	LXI D,w	37	STC	5B	MOV E,E	7E	MOV A,M	A1	ANA C	C4	CNZ a	EA	JPE	a
12	STAX D	39	DAD SP	5C	MOV E,H	7F	MOV A,A	A2	ANA D	C5	PUSH B	EB	XCHG	
13	INX D	3A	LDA a	5D	MOV E,L	80	ADD B	A3	ANA E	C6	ADI d	EC	CPE	a
14	INR D	3B	DCX SP	5E	MOV E,M	81	ADD C	A4	ANA H	C7	RST 0	EE	XRI	d
15	DCR D	3C	INR A	5F	MOV E,A	82	ADD D	A5	ANA L	C8	RZ	EF	RST	5
16	MVI D,d	3D	DCR A	60	MOV H,B	83	ADD E	A6	ANA M	C9	RET	F0	RP	
17	RAL	3E	MVI A,d	61	MOV H,C	84	ADD H	A7	ANA A	CA	JZ a	F1	POP	PSW
19	DAD D	3F	CMC	62	MOV H,D	85	ADD L	A8	XRA B	CC	CZ a	F2	JP	a
1A	LDAX D	40	MOV B,B	63	MOV H,E	86	ADD M	A9	XRA C	CD	CALL a	F3	DI	
1B	DCX D	41	MOV B,C	64	MOV H,H	87	ADD A	AA	XRA D	CE	ACI d	F4	CP	a
1C	INR E	42	MOV B,D	65	MOV H,L	88	ADC B	AB	XRA E	CF	RST 1	F5	PUSH	PSW
1D	DCR E	43	MOV B,E	66	MOV H,M	89	ADC C	AC	XRA H	D0	RNC	F6	ORI	d
1E	MVI E,d	44	MOV B,H	67	MOV H,A	8A	ADC D	AD	XRA L	D1	POP D	F7	RST	6
1F	RAR	45	MOV B,L	68	MOV L,B	8B	ADC E	AE	XRA M	D2	JNC a	F8	RM	
21	LXI H,w	46	MOV B,M	69	MOV L,C	8C	ADC H	AF	XRA A	D3	OUT d	F9	SPHL	
22	SHLD a	47	MOV B,A	6A	MOV L,D	8D	ADC L	B0	ORA B	D4	CNC a	FA	JM	a
23	INX H	48	MOV C,B	6B	MOV L,E	8E	ADC M	B1	ORA C	D5	PUSH D	FB	EI	
24	INR H	49	MOV C,C	6C	MOV L,H	8F	ADC A	B2	ORA D	D6	SUI d	FC	CM	a
25	DCR H	4A	MOV C,D	6D	MOV L,L	90	SUB B	B3	ORA E	D7	RST 2	FE	CPI	d
26	MVI H,d	43	MOV C,E	6E	MOV L,M	91	SUB C	B4	ORA H	D8	RC	FF	RST	7